

Previous Processors Compared to the

Cochlear™ Baha® 5 SuperPower



Sound Processors	Baha® Cordelle II System	Baha® 3 Power System (BP110)	Baha® 5 SuperPower System
Wearing Style	Bodyworn	Headworn	Headworn or Bodyworn
Year	1999	2011	2016
Actuator Size in mm (LxWxH)	29x23x10	N/A	28x17x14
Actuator Weight in grams	20g	N/A	14.4g
Sound Processor Size in mm (LxWxH)	90x34x26	36x22x12	39x9x48
Sound Processor Weight in grams	88g (incl. battery)	15.2g (excl. battery)	10.2g ¹
Processor Color Options	1 (3 colors on actuator)	6	4
Battery Type	9 volt	675	Rechargeable Lithium-Ion
Battery Life (standard rechargeable)	1 day	N/A	32 hours
Battery Life (compact rechargeable)	N/A	N/A	16 hours
Battery Life (disposable battery)	N/A	7-10 days	N/A
Processing Features			
SmartSound® iQ	No	No	Yes
Bluetooth® Smart Technology	No	No	Yes
# of Channels	1	12	17
Programs	1	3	4
Signal Processing	Analogue	Digital	Wireless/Digital
Wireless Streaming	No	No	Yes
Feedback Processing	No	Active Feedback Cancellation	Dual-Track Management
Datalogging	No	Yes	Yes
2.4 GHz Wireless	No	No	Yes
Made for iPhone®	No	No	Yes ²
Smart App	No	No	Yes ³
Control App	No	No	Yes
Support App	No	No	Yes

Sound Processors	Baha® Cordelle II System	Baha® 3 Power System (BP110)	Baha® 5 SuperPower System
Processing Features (cont.)			
Geotagging	No	No	Yes
Mixing Ratio Control	No	No	Yes
"Locate Device" Function	No	No	Yes
Low Battery Warning	No	Yes	Yes
Treble and Bass Adjust	Yes, tone switch	No	Yes
Accessories			
Tamper-proof Battery Doors	No	Yes	Yes
Sticker Accessories	No	No	Yes
Direct Audio Input	Yes	Yes	No
Battery Door Color Options	No	Yes	Yes
Wireless Remote Control	No	No	Yes ⁴
Wireless Bluetooth-Enabled Phone Clip	No	No	Yes
Wireless Mini Mic	No	No	Yes
Wireless TV Streamer	No	No	Yes
Telecoil	Yes	Yes, as accessory	Yes, in Mini Microphone 2+ ⁵
FM receiver	Yes, as accessory	Yes, as accessory	Yes, in Mini Microphone 2+ ⁵
Dust and Moisture Protection	No	Yes	Yes
Active Sound Programs Features			
Wind	No	Yes	Yes
Music	No	Yes	Yes
Noise	No	Yes	Yes
Scene Classifier	No	No	Yes

References

¹ Weight and size with medium Earhook and Compact Rechargeable battery module.

² The Cochlear Baha 5 SuperPower Sound Processor is compatible with iPhone 6 Plus, iPhone 6, iPhone 5s, iPhone 5c, iPhone 5, iPad Air 2, iPad Air, iPad (4th generation), iPad mini 3, iPad mini 2, iPad mini and iPod touch (5th generation) using iOS 7* or later.

³ The Cochlear Baha 5 Smart App is compatible with iPhone 6 Plus, iPhone 6, iPhone 5s, iPhone 5c, iPhone 5, iPad Air 2, iPad Air, iPad (4th generation), iPad mini 3, iPad mini 2, iPad mini and iPod touch (5th generation) using iOS 8.1 or later.

⁴ The Baha 5 SuperPower Sound Processor with the Cochlear Baha Remote Control (94765) and Cochlear Baha Remote Control 2 (94791).

⁵ Using the Mini Mic 2+ (P770848)

Cochlear Americas
 13059 East Peakview Avenue
 Centennial, CO 80111 USA
 Telephone: 1 303 790 9010
 Support: 1 800 483 3123

Cochlear Canada Inc.
 2500-120 Adelaide Street West
 Toronto, ON M5H 1T1 Canada
 Telephone: 1 416 972 5082
 Fax: 1 416 972 5083

©Cochlear Limited 2016. All rights reserved. Hear now. And always and other trademarks and registered trademarks are the property of Cochlear Limited or Cochlear Bone Anchored Solutions AB. The names of actual companies and products mentioned herein may be the trademarks of their respective owners.



BUN422 ISS1 FEB16

www.Cochlear.com/US

Hear now. And always



Cochlear®